








CONTACTOR&RELAY(IDC1-9-85)



Model	IDC1-9	IDC1-12	IDC1-18	IDC1-22	
					
Three pole contactors					
IEC-60947	AC coil	IDC1-9	IDC1-12	IDC1-18	
	DC coil	IDD1-9	IDD1-12	IDD1-18	
	AC1 Load	25A	25A	40A	40A
		200~240V	2.5KW 11A	3.5KW 13A	4.5KW 18A
		380~440V	4KW 9A	5.5KW 12A	7.5KW 18A
		500~550V	4KW 7A	7.5KW 12A	7.5KW 13A
	lth	690V	4KW 5A	7.5KW 9A	7.5KW 9A
		115V	20A	25A	30A
		230V	0.5HP	0.5HP	1HP
	UF508	200V	2HP	3HP	5HP
230V		2HP	3HP	5HP	
460V		5HP	7.5HP	10HP	
575V	7.5HP	10HP	15HP	15HP	
NEMA size					
	00	00	0	0	
					
Aux Contacts					
Four pole contactors	AC coil	IDC1-9/4	IDC1-12/4	IDC1-18/4	
	DC coil	IDD1-9/4	IDD1-12/4	IDD1-18/4	
	AC1(A)	20	20	25	
					
Overload relay					
Bimetal ID type					
	ID-22		Independent mounting unit		
	Rated current(A) 0.1-0.16 4-6 0.16-0.25 5-8 0.25-0.4 6-9 0.4-0.63 7-10 0.63-1 9-13 1-1.6 12-18 1.6-2.5 16-22 2.5-4				
Class 10A	IDK-22				
Class 20A	IDH-22/3				
Class 20A	IDK-22/L				

WELL CONTACTS CO

56, Pushpak Cascade Swathi Road, Shanthinagar, Bengaluru -560 077.

Tel-080 77726675, 77206675, 41169654 FAX-080 77726675

Email: wcblore_2007@yahoo.com, wellcontacts@yahoo.com